



ATC 用正面フライスアーバー (FMB)

(インチサイズ)

CODE	FIG.	D1	L1	C1	C3	H1	H2	W1	K1	G1	C4	C5	H3	H4	質量 kg																																													
BT40-FMB25.4 - 60	1	25.4	60	80	-	26	-	9.5	5	M12	33	23	10	12	2.9																																													
-FMB25.4 -105	2		105												4.1																																													
BT40-FMB38.1 - 60	3	38.1	60	85	28										26	6	15.9	9	M20	50	27	14	20	3.1																																				
-FMB38.1 - 90			90																					3.9																																				
※ BT45-FMB25.4 - 60	1	25.4	60	80	-																			26	-	9.5	5	M12	33	23	10	12																												
※ -FMB25.4 - 90	2		90																																																									
※ BT45-FMB38.1 - 60	3	38.1	60	85	28																												26	6	15.9	9	M20	50	27	14	20																			
※ -FMB38.1 -105			105																																																									
※ BT45-FMB38.1F- 60	6	38.1	60	110	-																																					26	-	9.5	5	M12	33	23	10	12										
BT50-FMB25.4 - 45	1		45																																																4.0									
-FMB25.4 - 90	2	25.4	90	80	-																																														26	-	9.5	5	M12	33	23	10	12	5.8
-FMB25.4 -150			150																																																									8.2
BT50-FMB38.1 - 45	3	38.1	45	85	28	26	6	15.9	9	M20	50	27	14	20																																														4.6
-FMB38.1 - 75			75																																																									6.0
-FMB38.1 -105	105	8.7																																																										
BT50-FMB38.1F- 75	6	38.1	75	110	-										26	-	9.5	5	M12	33	23	10	12																																					6.6

38.1Fはフランジ式PCD66.7(4ヶ所止メネジM12)です。

(ミリサイズ)

CODE	FIG.	D1	L1	C1	C3	H1	H2	W1	K1	G1	C4	C5	H3	H4	質量 Kg																																													
BT40-FMB27 - 60	1	27	60	80	-	26	-	12	6	M12	33	23	10	12	2.9																																													
-FMB27 -105	2		105												4.1																																													
BT40-FMB40 - 60	3	40	60	85	28										26	6	16	8.5	M20	50	27	14	20	3.1																																				
-FMB40 - 90			90																					3.9																																				
※ BT45-FMB27 - 60	1	27	60	80	-																			26	-	12	6	M12	33	23	10	12																												
※ -FMB27 -120	120																																																											
※ BT45-FMB40 - 60	3	40	60	85	28																												26	6	16	8.5	M20	50	27	14	20																			
※ -FMB40 -105			105																																																									
※ BT45-FMB40F- 65	6	40	65	110	-																																					26	-	12	6	M12	33	23	10	12										
BT50-FMB27 - 45	1		45																																																4.0									
-FMB27 - 90	1	27	90	80	-																																														26	-	12	6	M12	33	23	10	12	5.8
-FMB27 -150			150																																																									8.2
BT50-FMB40 - 45	3	40	45	85	28	26	6	16	8.5	M20	50	27	14	20																																														4.6
-FMB40 - 75	75		6.0																																																									
-FMB40 -105	4	105	8.7																																																									
BT50-FMB40F- 75	6	40	75	110	-										26	-	12	6	M12	33	23	10	12																																					6.6
BT50-FMB60 - 75	6		60																					140	-	25	-	25.4	12.5	-	-	-																												-

40Fはフランジ式PCD66.7(4ヶ所止メネジM12)です。