



ATC 用正面フライスアーバー (FMC)

(インチサイズ)

CODE	FIG.	D1	L1	C1	H1	W1	K1	G1	質量 kg
BT40-FMC25. 4- 60	1	25.4	60	70	20	9.5	6	M12	2.0
-FMC25. 4-105			105						3.0
※ BT45-FMC25. 4- 45			45						
※ -FMC25. 4- 90	3	25.4	90	70	20	9.5	6	M12	
※ -FMC25. 4-150			150						
※ BT45-FMC38. 1- 45			45						
※ -FMC38. 1- 75	3	38.1	75	85	22	15.9	7	M16	
※ -FMC38. 1-105			105						
BT50-FMC25. 4- 45			1						25.4
-FMC25. 4- 90	90	5.5							
-FMC25. 4-150	150	7.3							

(ミリサイズ)

CODE	FIG.	D1	L1	C1	C2	H1	W1	K1	G1	質量 Kg
BT30-FMC22- 45	1	22	45	45	-	18	10	5	M10	0.8
BT40-FMC22- 60			60							2.0
-FMC22-105			105							2.9
-FMC22-150	2		150							5.8
BT40-FMC27- 60	1	27	60	70	-	20	12	6	M12	2.9
-FMC27-105	2		105							4.1
BT40-FMC32- 60	1	32	60	85	-	22	14	7	M16	3.1
-FMC32- 90	2		90							3.9
※ BT45-FMC22- 45	1	22	45	45	-	18	10	5	M10	
※ -FMC22-120	2		120							
※ BT45-FMC27- 60	1	27	60	70	-	20	12	6	M12	
※ -FMC27-105	2		105							
※ BT45-FMC32- 60	3	32	60	85	-	22	14	7	M16	
※ -FMC32-105			105							
BT50-FMC22- 60	1	22	60	45	-	18	10	5	M10	4.2
-FMC22-105			105							4.7
-FMC22-150			150							5.3
-FMC22-200			200							7.5
-FMC22-250			250							8.5
-FMC22-300			300							9.5
-FMC22-400			400							11.5
-FMC22-500	500	13.5								
BT50-FMC27- 45	2	27	45	70	-	20	12	6	M12	4.1
-FMC27- 90			90							5.5
-FMC27-150			150							7.3
BT50-FMC32- 45	3	32	45	85	-	22	14	7	M16	4.2
-FMC32- 75			75							5.5
-FMC32-105			105							6.8
-FMC32-150			150							8.8
-FMC32-200			200							10.9
-FMC32-250			250							13.2
-FMC32-300	300									

付属ボルトは、キャップボルトとなります。T型締付ボルトは、別売になります。